



| Turn | MBLN130-xxS | | | MBLN130-xxL | | |
|------|-------------|------------|-------|-------------|------------|-------|
| | Max Amps | Resistance | RPM/V | Max Amps | Resistance | RPM/V |
| 10 | 22 | 0.0210 | 10077 | | | |
| 11 | 19 | 0.0279 | 9145 | | | |
| 12 | 18 | 0.0315 | 7800 | 20 | 0.0387 | 4834 |
| 13 | 16 | 0.0370 | 7200 | 18 | 0.0454 | 4462 |
| 14 | 15 | 0.0429 | 6686 | 17 | 0.0526 | 4143 |
| 15 | 14 | 0.0493 | 6240 | 16 | 0.0604 | 3867 |
| 16 | 13 | 0.0561 | 5850 | 15 | 0.0687 | 3625 |
| 17 | 13 | 0.0633 | 5506 | 14 | 0.0776 | 3412 |
| 18 | 12 | 0.0710 | 5200 | 13 | 0.0870 | 3223 |
| 19 | 11 | 0.0791 | 4926 | 12 | 0.0969 | 3053 |
| 20 | 11 | 0.0876 | 4680 | 12 | 0.1074 | 2900 |
| 21 | 10 | 0.0966 | 4457 | 11 | 0.1184 | 2762 |
| 22 | 10 | 0.1060 | 4255 | 11 | 0.1300 | 2637 |
| 23 | 9 | 0.1159 | 4070 | 10 | 0.1420 | 2522 |
| 24 | 9 | 0.1261 | 3900 | 10 | 0.1547 | 2417 |
| 25 | 9 | 0.1369 | 3744 | 9 | 0.1678 | 2320 |
| 26 | 8 | 0.1480 | 3600 | 9 | 0.1815 | 2231 |
| 27 | 8 | 0.1597 | 3467 | 9 | 0.1958 | 2148 |
| 28 | 8 | 0.1717 | 3343 | 8 | 0.2105 | 2072 |
| 29 | 7 | 0.1842 | 3228 | 8 | 0.2258 | 2000 |
| 30 | 7 | 0.1971 | 3120 | 8 | 0.2417 | 1934 |
| 31 | 7 | 0.2105 | 3019 | 8 | 0.2580 | 1871 |
| 32 | 7 | 0.2243 | 2925 | 7 | 0.2750 | 1813 |
| 33 | 6 | 0.2385 | 2836 | 7 | 0.2924 | 1758 |
| 34 | 6 | 0.2532 | 2753 | 7 | 0.3104 | 1706 |
| 35 | 6 | 0.2683 | 2674 | 7 | 0.3289 | 1657 |
| 36 | 6 | 0.2838 | 2600 | 7 | 0.3480 | 1611 |
| 37 | 6 | 0.2998 | 2530 | 6 | 0.3676 | 1568 |
| 38 | 6 | 0.3162 | 2463 | 6 | 0.3877 | 1526 |
| 39 | 5 | 0.3331 | 2400 | 6 | 0.4084 | 1487 |
| 40 | 5 | 0.3504 | 2340 | 6 | 0.4296 | 1450 |
| 41 | 5 | 0.3682 | 2283 | 6 | 0.4514 | 1415 |
| 59 | | | | 4 | 0.94 | 979 |
| 80 | 2.6 | 1.3680 | 1195 | | | |
| 156 | | | | 1.5 | 5.91 | 316 |